



# A7600 Series\_ FTP(S)\_Application Note

LTE Module

## **SIMCom Wireless Solutions Limited**

Building B, SIM Technology Building, No.633, Jinzhong Road

Changning District, Shanghai P.R. China

Tel: 86-21-31575100

support@simcom.com

www.simcom.com

<b>Document Title:</b>	A7600 Series_FTP(S)_Application Note
<b>Version:</b>	1.00
<b>Date:</b>	2020.6.19
<b>Status:</b>	Released

## GENERAL NOTES

SIMCOM OFFERS THIS INFORMATION AS A SERVICE TO ITS CUSTOMERS, TO SUPPORT APPLICATION AND ENGINEERING EFFORTS THAT USE THE PRODUCTS DESIGNED BY SIMCOM. THE INFORMATION PROVIDED IS BASED UPON REQUIREMENTS SPECIFICALLY PROVIDED TO SIMCOM BY THE CUSTOMERS. SIMCOM HAS NOT UNDERTAKEN ANY INDEPENDENT SEARCH FOR ADDITIONAL RELEVANT INFORMATION, INCLUDING ANY INFORMATION THAT MAY BE IN THE CUSTOMER'S POSSESSION. FURTHERMORE, SYSTEM VALIDATION OF THIS PRODUCT DESIGNED BY SIMCOM WITHIN A LARGER ELECTRONIC SYSTEM REMAINS THE RESPONSIBILITY OF THE CUSTOMER OR THE CUSTOMER'S SYSTEM INTEGRATOR. ALL SPECIFICATIONS SUPPLIED HEREIN ARE SUBJECT TO CHANGE.

## COPYRIGHT

THIS DOCUMENT CONTAINS PROPRIETARY TECHNICAL INFORMATION WHICH IS THE PROPERTY OF SIMCOM WIRELESS SOLUTIONS LIMITED. COPYING, TO OTHERS AND USING THIS DOCUMENT, ARE FORBIDDEN WITHOUT EXPRESS AUTHORITY BY SIMCOM. OFFENDERS ARE LIABLE TO THE PAYMENT OF INDEMNIFICATIONS. ALL RIGHTS RESERVED BY SIMCOM IN THE PROPRIETARY TECHNICAL INFORMATION, INCLUDING BUT NOT LIMITED TO REGISTRATION GRANTING OF A PATENT, A UTILITY MODEL OR DESIGN. ALL SPECIFICATION SUPPLIED HEREIN ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.

### **SIMCom Wireless Solutions Limited**

Building B, SIM Technology Building, No.633 Jinzhong Road, Changning District, Shanghai P.R. China

Tel: +86 21 31575100

Email: [simcom@simcom.com](mailto:simcom@simcom.com)

### **For more information, please visit:**

<https://www.simcom.com/download/list-863-en.html>

### **For technical support, or to report documentation errors, please visit:**

<https://www.simcom.com/ask/> or email to: [support@simcom.com](mailto:support@simcom.com)

**Copyright © 2020 SIMCom Wireless Solutions Limited All Rights Reserved.**

# About Document

## Version History

Revision	Date	Chapter	Description
V1.00	2020.06.19		New version

## Scope

This document presents the AT Command Set for SIMCom A7600 Series, including A7600XX-XXXX, A5360E, and A7670X.

# Contents

<b>About Document .....</b>	<b>2</b>
Version History .....	2
Scope .....	2
<b>Contents .....</b>	<b>3</b>
<b>1 Introduction.....</b>	<b>4</b>
1.1 Purpose of the document.....	4
1.2 Related documents .....	4
1.3 Conventions and abbreviations .....	4
1.4 The process of Using FTP(S) AT Commands .....	5
1.5 Error Handling.....	6
1.5.1 Executing FTP(S) AT Commands Fails .....	6
1.5.2 PDP Activation Fails .....	6
1.5.3 Error Response of FTP(S) Server .....	6
<b>2 AT Commands for FTP(S) .....</b>	<b>7</b>
<b>3 FTP(S) Examples .....</b>	<b>8</b>
3.1 FTP Function .....	8
3.1.1 Download a file from FTP server to module/Upload a file to FTP server from module .....	9
3.1.2 Download a file from FTP server to serial port/Upload a file from serial port to FTP server .....	10
3.1.3 Directory Operations .....	11
3.2 FTPS Function .....	12
3.2.1 Download a file from FTPS server to module/Upload a file to FTPS server from module .....	12
3.2.2 Download a file from FTPS server to serial port/Upload a file from serial port to FTPS server .....	13
3.2.3 Directory Operations .....	15
<b>4 Appendix .....</b>	<b>17</b>
4.1 Summary of Error Codes .....	17

# 1 Introduction

## 1.1 Purpose of the document

Based on module AT command manual, this document will introduce FTP(S) application process. Developers could understand and develop application quickly and efficiently based on this document.

## 1.2 Related documents

[1] A7600 Series\_AT Command Manual

## 1.3 Conventions and abbreviations

In this document, the GSM engines are referred to as following term:

ME (Mobile Equipment);

MS (Mobile Station);

TA (Terminal Adapter);

DCE (Data Communication Equipment) or facsimile DCE (FAX modem, FAX board);

In application, controlling device controls the GSM engine by sending AT Command via its serial interface. The controlling device at the other end of the serial line is referred to as following term:

TE (Terminal Equipment);

DTE (Data Terminal Equipment) or plainly "the application" which is running on an embedded system;

Other Conventions:


PDP(Packet Data Protocol);

FTP(File Transfer Protocol);

SSL(Secure Sockets Layer);

TLS(Transport Layer Security);

## 1.4 The process of Using FTP(S) AT Commands



## 1.5 Error Handling

### 1.5.1 Executing FTP(S) AT Commands Fails

When executing FTP(S) AT commands, if **ERROR** response is received from the module, please check whether the U(SIM) card is inserted and whether it is **+CPIN: READY** returned when executing **AT+CPIN?**.

### 1.5.2 PDP Activation Fails

If it is failed to activate a PDP context with **AT+CGACT** command, please check the following configurations:

1. Query the PS domain status by **AT+CGREG?** and make sure the PS domain has been registered.
2. Query the PDP context parameters by **AT+CGDCONT?** and make sure the APN of the specified PDP context has been set.
3. Make sure the specified PDP context ID is neither used by PPP nor activated by **AT+CGACT** command.

If all above configurations are correct, but activating the PDP context by **AT+CGACT** command still fails, please reboot the module to resolve this issue. After rebooting the module, please check the configurations mentioned above for at least.

### 1.5.3 Error Response of FTP(S) Server

When the **CFTPSXXX: <errorcode>** is not 0, it indicates an error code replied from FTP(S) server.

For example, if **<errorcode>** is 1, ssl configure may be wrong. If **<errorcode>** is 17, the file or directory may not exist. For more details, please refer to A7600 Series\_AT Command Manual \_V1.01.08.

## 2 AT Commands for FTP(S)

Command	Description
<b>AT+CFTPSSTART</b>	Start FTP(S) service
<b>AT+CFTPSSTOP</b>	Stop FTP(S) Service
<b>AT+CFTPSLOGIN</b>	Login to a FTP(S)server
<b>AT+CFTPSLOGOUT</b>	Logout a FTP(S) server
<b>AT+CFTPSLIST</b>	List the items in the directory on FTP(S) server
<b>AT+CFTPSMKD</b>	Create a new directory on FTP(S) server
<b>AT+CFTPSRMD</b>	Delete a directory on FTP(S) server
<b>AT+CFTPSCWD</b>	Change the current directory on FTP(S) server
<b>AT+CFTPSPWD</b>	Get the current directory on FTP(S) server
<b>AT+CFTPSDELE</b>	Delete a file on FTP(S) server
<b>AT+CFTPSGETFILE</b>	Download a file from FTP(S) server to module
<b>AT+CFTPSPUTFILE</b>	Upload a file from module to FTP(S) server
<b>AT+CFTPSGET</b>	Get a file from FTP(S) server to serial port
<b>AT+CFTPSPUT</b>	Put a file to FTP(S) server through serial port
<b>AT+CFTPSSIZE</b>	Get the file size on FTP(S) server
<b>AT+CFTPSSINGLEIP</b>	Set FTP(S) data socket address type
<b>AT+CFTPSTYPE</b>	Set the transfer type on FTP(S) server
<b>AT+CFTPSSLCFG</b>	Set the SSL context id for FTPS session

For more detailed information, please refer to *A7600 Series\_AT Command Manual*.



## 3 FTP(S) Examples

Before all FTP(S) related operations, we should ensure the following:  
Ensure network is available:

**AT+CSQ**

+CSQ: 23,0

OK

**AT+CREG?**

+CREG: 0,1

OK

**AT+CGREG?**

+CGREG: 0,1

OK

**AT+CPSI?**

+CPSI:

LTE,Online,460-00,0x333C,39589680,308,EUT

RAN-BAND3,1350,5,0,0,54,0,22

OK

//In WCDMA/GSW,you need to continue to  
execute the following instructions

**AT+CGDCONT=cid,"ip","APN"**

OK

**AT+CGACT=1,cid**

OK

**AT+CGACT?**

+CGACT: 1,1

OK

### 3.1 FTP Function

### 3.1.1 Download a file from FTP server to module/Upload a file to FTP server from module

//Example of FTP upload/download

**AT+CFTPSSTART**

//Start FTP service

OK

+CFTPSSTART: 0

**AT+CFTPSLOGIN="255.255.255.255",21,"user name","password",0**

//Login to a FTP server

OK

+CFTPSLOGIN: 0

**AT+CFTPSLIST="/"**

//List all ms of directory "/"

OK

+CFTPSLIST: DATA,175

-rw-r--r-- 1 ftp ftp 121 Mar 11 16:24 124.txt

drwxr-xr-x 1 ftp ftp 0 Jan 13 2020 TEST113

drwxr-xr-x 1 ftp ftp 0 Jan 19 2020 TEST1155

+CFTPSLIST: 0

**AT+CFTPSPWD**

//Get current directory of FTP server

OK

+CFTPSPWD: "/"

**AT+CFTPSGETFILE="124.txt"**

//Download a file from FTP server to module.

OK

+CFTPSGETFILE: 0

**AT+CFTPSPUTFILE="124.TXT"**

//Upload a file to FTP server from module

OK

+CFTPSPUTFILE: 0

**AT+CFTPSLOGOUT**

//Logout FTP server

OK

+CFTPSLOGOUT: 0

**AT+CFTPSSTOP**

//Stop FTP server

OK

+CFTPSSTOP: 0

### 3.1.2 Download a file from FTP server to serial port/Upload a file from serial port to FTP server

//Example of FTP upload/download

**AT+CFTPSSTART**

//Start FTP service

OK

+CFTPSSTART: 0

**AT+CFTPSLOGIN="255.255.255.255",21,"user name","password",0** //Login to a FTP server

OK

+CFTPSLOGIN: 0

**AT+CFTPSLIST="/"**

//List all ms of directory "/"

OK

+CFTPSLIST: DATA,175

-rw-r--r-- 1 ftp ftp 121 Mar 11 16:24  
124.txt

-rw-r--r-- 1 ftp ftp 3 Mar 19 17:10  
test1131.txt

drwxr-xr-x 1 ftp ftp 0 Jan 13  
2020 TEST113

drwxr-xr-x 1 ftp ftp 0 Jan 19  
2020 TEST1155

+CFTPSLIST: 0

**AT+CFTPSPWD**

//Get current directory of FTP server

OK

+CFTPSPWD: "/"

**AT+CFTPSGET="test1131.txt"**

//Download a file from FTP server to serial port

OK

+CFTPSGET: DATA,3

321

+CFTPSGET: 0

**AT+CFTPSPUT="test1131.txt"**

//Upload a file to FTP server from serial port

> (input the data, and use ctrl+Z to complete upload)

OK

+CFTPSPUT: 0

```

AT+CFTPSPUT="test1131.txt",3 //Upload a file to FTP server from serial port by
> (input the data,when the length is 3,Upload limiting the length.
will complete automatically)
OK

+CFTPSPUT: 0

AT+CFTPSLOGOUT //Logout FTP server
OK

+CFTPSLOGOUT: 0
AT+CFTPSSTOP //Stop FTP server
OK

+CFTPSSTOP: 0

```

### 3.1.3 Directory Operations

```

//Example of FTP directory operations
AT+CFTPSSTART //Start FTP service
OK

+CFTPSSTART: 0
AT+CFTPSLOGIN="255.255.255.255",21,"user //Login to a FTP server
name","password",0
OK

+CFTPSLOGIN: 0
AT+CFTPSLIST="/" //List all ms of directory "/"
OK

+CFTPSLIST: DATA,175
-rw-r--r-- 1 ftp ftp      121 Mar 11 16:24
124.txt
-rw-r--r-- 1 ftp ftp      3 Mar 19 17:10
test1131.txt
drwxr-xr-x 1 ftp ftp      0 Jan 13
2020 TEST113
drwxr-xr-x 1 ftp ftp      0 Jan 19
2020 TEST1155

+CFTPSLIST: 0
AT+CFTPSPWD //Get current directory of FTP server

```

OK

+CFTPSPWD: "/"

**AT+CFTPSPWD="TEST1129"**

//Create a new directory

OK

+CFTPSPWD: 0

**AT+CFTPSPWD="TEST1129"**

//Change to the specified directory

OK

+CFTPSPWD: 0

**AT+CFTPSPWD**

//Get current directory of FTP server

OK

+CFTPSPWD: "/TEST1129"

**AT+CFTPSPWD**

//Change to the specified directory

OK

+CFTPSPWD: "/"

**AT+CFTPSPWD="/TEST1129"**

//Delete the specified directory

OK

+CFTPSPWD: 0

**AT+CFTPSPWD**

//Logout FTP server

OK

+CFTPSPWD: 0

**AT+CFTPSPWD**

//Stop FTP server

OK

+CFTPSPWD: 0

## 3.2 FTPS Function

### 3.2.1 Download a file from FTPS server to module/Upload a file to FTPS server from module

//Example of FTP(S) upload/download

**AT+CFTPSTART**

///Start FTP service

OK

```

+CFTPSSTART: 0
AT+CFTPSLOGIN="255.255.255",990,"use //Login to a Implicit FTPS server.
rname","password"
OK

+CFTPSLOGIN: 0
AT+CFTPSLIST="/" //List all ms of directory "/"
OK

+CFTPSLIST: DATA,175
-rw-r--r-- 1 ftp ftp      121 Mar 11 16:24
124.txt
drwxr-xr-x 1 ftp ftp      0 Jan 13
2020 TEST113
drwxr-xr-x 1 ftp ftp      0 Jan 19
2020 TEST1155

+CFTPSLIST: 0
AT+CFTPSPWD //Get current directory of FTP server
OK

+CFTPSPWD: "/"
AT+CFTPSGETFILE="124.txt" //Download a file from FTP server to module.
OK

+CFTPSGETFILE: 0
AT+CFTPSPUTFILE="124.TXT" //Upload a file to FTP server from module
OK

+CFTPSPUTFILE: 0
AT+CFTPSLOGOUT //Logout FTP server
OK

+CFTPSLOGOUT: 0
AT+CFTPSSTOP //Stop FTP server
OK

+CFTPSSTOP: 0

```

### 3.2.2 Download a file from FTPS server to serial port/Upload a file from serial port to FTPS server

//Example of FTP(S) upload/download

```

AT+CFTPSSTART                                     //Start FTP service
OK

+CFTPSSTART: 0
AT+CFTPSLOGIN="255.255.255.255",990,"use //Login to a Implicit FTPS server.
rname","password"
OK

+CFTPSLOGIN: 0
AT+CFTPSLIST="/"                                  //List all ms of directory "/"
OK

+CFTPSLIST: DATA,175
-rw-r--r-- 1 ftp ftp          121 Mar 11 16:24
124.txt
-rw-r--r-- 1 ftp ftp          3 Mar 19 17:10
test1131.txt
drwxr-xr-x 1 ftp ftp          0 Jan 13
2020 TEST113
drwxr-xr-x 1 ftp ftp          0 Jan 19
2020 TEST1155

+CFTPSLIST: 0
AT+CFTPSPWD                                       //Get current directory of FTP server
OK

+CFTPSPWD: "/"
AT+CFTPSGET="test1131.txt"                       //Downloda a file from FTP server to serial port
OK

+CFTPSGET: DATA,3
321
+CFTPSGET: 0
AT+CFTPSPUT="test1131.txt"                       //Upload a file to FTP server from serial port
> (input the data,and use ctrl+Z to complete
upload)
OK

+CFTPSPUT: 0
AT+CFTPSPUT="test1131.txt",3                     //Upload a file to FTP server from serial port by
> (input the data,when the length is 3,Upload limiting the length.
will complete automatically)
OK

+CFTPSPUT: 0

```

```

AT+CFTPSLOGOUT                                //Logout FTP server
OK

+CFTPSLOGOUT: 0
AT+CFTPSSTOP                                  //Stop FTP server
OK

+CFTPSSTOP: 0

```

### 3.2.3 Directory Operations

```

//Example of FTP(S) directory operations
AT+CFTPSSTART                                //Start FTP service
OK

+CFTPSSTART: 0
AT+CFTPSLOGIN="255.255.255.255",660,"use //Login to a Implicit FTPS server
rname","password"
OK

+CFTPSLOGIN: 0
AT+CFTPSLIST="/"                             //List all ms of directory "/"
OK

+CFTPSLIST: DATA,175
-rw-r--r-- 1 ftp ftp          121 Mar 11 16:24
124.txt
-rw-r--r-- 1 ftp ftp          3 Mar 19 17:10
test1131.txt
drwxr-xr-x 1 ftp ftp          0 Jan 13
2020 TEST113
drwxr-xr-x 1 ftp ftp          0 Jan 19
2020 TEST1155

+CFTPSLIST: 0
AT+CFTPSPWD                                  //Get current directory of FTP server
OK

+CFTPSPWD: "/"
AT+CFTPSMKD="TEST1129"                       //Create a new directory
OK

+CFTPSMKD: 0

```



**AT+CFTPSCWD="TEST1129"**

//Change to the specified directory

OK

**+CFTPSCWD: 0**

**AT+CFTPSPWD**

//Get current directory of FTP server

OK

**+CFTPSPWD: "/TEST1129"**

**AT+CFTPSCWD**

//Change to the specified directory

OK

**+CFTPSCWD: "/"**

**AT+CFTP SRMD="/TEST1129"**

//Delete the specified directory

OK

**+CFTP SRMD: 0**

**AT+CFTPSLOGOUT**

//Logout FTP server

OK

**+CFTPSLOGOUT: 0**

**AT+CFTPSSTOP**

//Stop FTP server

OK

**+CFTPSSTOP: 0**

## 4 Appendix

### 4.1 Summary of Error Codes

Code of <errcode>	Description
0	Success
1	SSL alert
2	Unknown error
3	Busy
4	Connection closed by server
5	Timeout
6	Transfer failed
7	File not exists or any other memory error
8	Invalid parameter
9	Operation rejected by server
10	Network error
11	State error
12	Failed to parse server name
13	Create socket error
14	Connect socket failed
15	Close socket failed
16	SSL session closed
17	File error, file not exist or other error.